

How to configure PPPoE on ADSL Modem Router?

It is suitable for : **ND150, ND300**

STEP-1:

Connect to the Modem Router by cable or wireless at first. Type in 192.168.1.1 in the address field of web browser and then press **Enter** key.

→ C ③ 192.168.1.1

STEP-2:

Then below window will pop up that requires you to enter valid User Name and Password.

Enter **admin** for User Name and Password, both in lower case letters. Then click **LOGIN** button or press **Enter** key.

_	USER LOGIN
User Name: Password:	admin
	Login Reset

STEP-3:

Now you have logged into the web interface of the Modem Router. Then click **Setup->WAN**, you can setup the PPPoE connection.

Note: VPI and VCI are provided by the ISP.

Status	Easy Setup	Setup Advan	ced Service	Firewall Mainte	nance
WAN		WAN Configuration This page is used to config connect type of PPPoE and) ure the parameters for the V d PPPoA only is "Manual", th	(AN interface of your ADSL and(or) e "Connect" and "Disconnect" buth	Ethernet Modem/Router. Note : When on will be enable.
> WAN > Auto PVC		WAN Physical Type: O ADSL WAN Ethernet WAN			
> ATM		Default Route Selection: O Auto Specified			
> ADSL		VPI:	0	VCI:	
LAN WLAN		Encapsulation:	οuc	VC-Mux 2	
		Channel Mode:	PPPoE	Enable NAPT:	
		Enable IGMP:			
		IP Protocol:	lpv4 🗸		

STEP-4:

After chose the PPPoA/PPPoE type, you should enter the account and password provided by you ISP in the corresponding field.

PPP Settings:	4				
User Name:		Password:			
Туре:	Continuous	Idle Time (min):			
WAN IP Settings:					
Type:	Fixed IP	OHCP			
Local IP Address:		Remote IP Address:			
NetMask:					
Default Route:	O Disable	Enable	O Auto		
Uppumbered:					
Connect Disconnect	Add Modify Delet	e Undo Refresh			