

How to setup N200RE V3 Multi-SSID?

N100RE, N150RH, N150RT, N151RT, N200RE, N210RE, N300RT, It is suitable for : N301RT , N300RH, N302R Plus, A702R, A850, A3002RU

Application introduction: Multi-SSID allows users to create multiple WiFi networks with different priority. It is good for access control

and data privacy.

Take N200RE-V3 as an example.

STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering

http://192.168.0.1 into the address bar of your browser.

€	\rightarrow	C' 🛈		Q 192.168.0.1										\rightarrow		
						- A.S.A.										- 194

Note:

The default access address varies depending on the actual situation. Please find it on the bottom label of the product.

STEP-2:

User Name and Password are required, by default both are **admin** in lowercase letter. Click **LOGIN**.

USER LOGIN



STEP-3:

First, the Easy Setup page will turn up for basic and quick settings, click Advanced Setup.



Connect Status		
	Connect Status	DHCP
Internet Setting		
	WAN Type	DHCP Client •
Wireless Setting		
	SSID	TOTOLINK_N200RE
	Pre-Shared Key	12345678 (length range is 8-63)
IPTV Settings		
	IPTV	Disable v
		Apply Refresh
	Convria	

STEP-4:

Click Wireless Setting->Multiple SSID1 on the left navigation bar.



STEP-5:

Choose Enable to add more SSID. Then enter SSID, choose Encryption method, define password, click Apply.

Multiple SSID 1

Multiple SSID 1	Enabled ~
SSID	TOTOLINK_N200RE1
Access	LAN+WAN ~
Broadcast SSID	Enabled ~
Encryption	WPA-Mixed ~
Limit Client AP(1-32)	32
Download:	0 Mbps (0:Unlimit)
Upload:	0 Mbps (0:Unlimit)
Authentication Mode	O Enterprise (RADIUS) Personal (Pre-Shared Key)
WPA Cipher Suite	
Pre-Shared Key Format	Passphrase V









